Pioneer

GM-DX874

Class-FD 4-Channel Bridgeable Amplifier with Bass Boost Remote

The Audiophile Selection: Where Hi-Res Amplification Takes Center

Designed for those who crave power, our GM-D Series brings high power capabilities to the forefront. GM-D series maintains a clean and pure signal path, minimizing distortion and maximizing sonic fidelity. It breathes life into your favorite tracks, unveiling intricate details and nuances that were once hidden, creating an immersive listening experience like no other. With its 1,200W of power and a frequency response of up to 50,000 Hz, GM-DX874 commands your music with authority and ensuring breathtaking performance and crystal-clear playback of high-resolution audio. Crafted using high-grade electronic components and featuring gold-plated RCA connections, the GM-DX874 amplifier maximizes signal integrity and minimizes distortion, allowing for exceptional audio reproduction.

Specifications

Amplifier Class	Class FD
No. of Channels	4/3/2
Max.power output	200 W x 4 (4Ω) 300 W x 4 (2Ω) 600 W x 2 (4Ω Bridged)
RMS power output	100 W x 4 (4Ω) 150 W x 4 (2Ω) 125 W x 4 (1Ω) 300 W x 2 (4Ω Bridged)
Frequency Response	10 Hz to 50 kHz
Impedance	1Ω to 8Ω
Total Harmonic Distortion(THD)	
S/N Ratio	>95 dB
RCA Outputs (Press- Through)	Yes (A-Ch)
Speaker Level Input	Yes
Automatic Signal Sensing and Turn-On	Yes
Crossover Type	Variable HPF/LPF
Crossover Frequency	40 Hz to 500 Hz
Bass Boost Frequency	50 Hz
Baas Boost Level	0 dB to 18 dB
Bass Boost Remote	Yes (B-Ch)
Dimensions (W x H x D)	252 mm x 60 mm x 215 mm