

Class-FD 4-Channel Bridgeable Amplifier with Bass Boost Remote

Amplify Your Experience: Where Amplification Takes Center Stage

Designed for those who crave power, our GM-D Series brings high power capabilities to the forefront. GM-D series maintains a clean and pure signal path, minimizing distortion and maximizing sonic fidelity. It breathes life into your favorite tracks, unveiling intricate details and nuances that were once hidden, creating an immersive listening experience like no other. With a high-power output of 1200W, GM-D8704 packs a punch, delivering intense and immersive sound for your car audio system. Its four channels provide the flexibility to connect and power a variety of speakers, allowing you to create a custom sound setup tailored to your preferences. Whether you're amplifying a pair of front and rear speakers or incorporating a subwoofer for added depth, GM-D8704 takes your audio experience to the next level.

Specifications

Amplifier Class	Class-FD
No. of Channels	4/3/2
Max.power output	200 W x 4 (4Ω) 300 W x 4 (2Ω) 600 W x 2 (4Ω Bridged)
RMS power output	100 W x 4 (4Ω) 150 W x 4 (2Ω) 125 W x 4 (1Ω) 300 W x 2 (4Ω Bridged)
Frequency Response	10 Hz to 50 kHz
Impedance	1Ω to 8Ω
Total Harmonic Distortion(THD)	
S/N Ratio	>95 dB
RCA Outputs (Press- Through)	Yes (A-Ch.)
Speaker Level Input	Yes
Automatic Signal Sensing and Turn-On	Yes
Crossover Type	Variable HPF/LPF
Crossover Frequency	40 Hz to 500 Hz
Bass Boost Frequency	50 Hz
Baas Boost Level	0 dB to 18 dB
Bass Boost Remote	Yes (B-Ch.)
Dimensions (W x H x D)	252 mm x 60 mm x 215 mm